

## A6-USD4

### A6 Option Switch Settings (AC 110V for 5V Enable)

Supported bill US\$ 1, 5, 10, 20, (old 5, 10, 20), (new 20) 4bills.

A6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject US\$ 1	ON											
Accept US\$ 1	OFF											
Reject US\$ 5		ON										
Accept US\$ 5		OFF										
Reject US\$ 10			ON									
Accept US\$ 10			OFF									
Reject US\$ 20				ON								
Accept US\$ 20				OFF								
Reserved					ON							
Reserved					OFF							
High Acceptance						ON						
High Security						OFF						
Harness disable							ON					
Harness enable							OFF					
Enable Active Low								ON				
Enable Active High								OFF				
1 pulse / one dollar									OFF	OFF		
2 pulse / one dollar									ON	OFF		
4 pulse / one dollar									OFF	ON		
20 pulse / one dollar									ON	ON		
Pulse Speed	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

